

Polycom IP 6000 Firmware Upgrade

Upgrade to firmware version 3.3.5.0247

Menu / Settings / Advanced / Administration Settings / Network Configuration / Server Menu

- Configure the DHCP menu
3.x firmware: **Menu / Settings / Advanced / Admin Settings / Network Configuration / DHCP Menu**
 - Boot Server: **Static**
 - BootSrv Type: **IP Address**
- Configure the Provisioning Server menu
 - Server Type: **HTTP**
 - Server Address: **140.242.64.35/335**

Upgrade to firmware version 4.0.8.1608

Menu / Settings / Advanced / Administration Settings / Network Configuration / Server Menu

- Configure the DHCP menu
3.x firmware: **Menu / Settings / Advanced / Admin Settings / Network Configuration / DHCP Menu**
 - Boot Server: **Static**
 - BootSrv Type: **IP Address**
- Configure the Provisioning Server menu
 - Server Type: **HTTP**
 - Server Address: **140.242.64.35/408**

THIS PROCESS TAKES 15-20 MINUTES, THE PHONE WILL REBOOT MULTIPLE TIMES, DON'T PANIC

Reset the phone

Reset the phone when this is complete to set the provisioning details back to default

Menu / Settings / Advanced / Admin Settings / Reset to Defaults / Reset to Factory